

# Petrol Silent Inverter Generator (3.5kW)

- 3500W max / 3200W rated output suitable for tools, appliances, and site equipment
- Pure sine wave technology delivers clean, stable power suitable for sensitive electronics such as phones, laptops, and TVs
- Digital display panel shows voltage, frequency, and run time at a glance
- Multiple outlet options including AC, DC, and USB Type A & C for flexible connectivity
- Parallel-ready capability allows two units to be connected for higher power output (parallel kit sold separately)
- Built-in safety protection including automatic shutdown, low oil warning LED, and overload protection
- Supplied with user manual, oil funnel, and spark plug wrench
- Material: Aluminium, Iron
- Finish: Powder Coated
- Power Source: Petrol Powered
- Frequency: 50Hz
- AC Output Voltage: 240V
- Rated Output Voltage: 3200W
- Max Output Voltage: 3500W
- Rated Current: 13.9A
- Power Factor: 1.0
- Performance Class: G2
- DC Voltage / DC Current: 12V/3.8A
- Noise: 67 (dB/7m) idle
- Fuel Type: Gasoline
- Petrol Type: More than RQ90
- Fuel Tank Capacity: 5L
- Working Time: Up to 7.5 (h/25%Load)
- Fuel Consumption: 340 (g/kw.h)
- Engine: UPI65A
- Engine Type: Single Cylinder, 4 Stroke OHV Air-Cooled
- Displacement Capacity: 149cc
- Lubrication Oil: SAE 10W-30
- Starting System: Easy Pulling
- Low Oil Shutdown: YES
- Engine RPM: 5000 RPM
- Lubrication Method: Splash Type
- USB: 1type A+1 type C
- Certification: CE EURO-V
- IP Rating: IP23M



Code	Overall Size LxWxH (mm)	Unit Weight (kg)
V4300	500x300x450	23